

IN THE CLAIMS:

1. An apparatus for processing data in a spread spectrum system, comprising:  
a decimation circuit having an associated decimation factor;  
a memory coupled to said decimation circuit; and  
an interpolation circuit coupled to said memory, said interpolation circuit  
having an associated interpolation factor;  
wherein said decimation circuit decimates a data rate of received data by said  
decimation factor to a decimated rate and stores said received data into said memory at  
said decimated rate; and  
wherein said interpolation circuit interpolates said decimated rate by said  
interpolation factor to an interpolated rate and retrieves said received data from said  
memory at said interpolated rate.
2. The apparatus of claim 1, further comprising:  
a communication processor coupled to said interpolation circuit for receiving  
data from said memory at said interpolated rate.
3. The apparatus of claim 1, further comprising:  
a dedicated controller for controlling data retrieval from said memory.
4. The apparatus of claim 1, further comprising:  
a micro-processor for controlling data retrieval from said memory.
5. The apparatus of claim 1, wherein said decimation factor is programmable by  
configuring said decimation circuit.
6. The apparatus of claim 1, wherein said decimation factor is hard-coded into  
said decimation circuit.

7. The apparatus of claim 1, wherein said interpolation factor is programmable by configuring said interpolation circuit.
8. The apparatus of claim 1, wherein said interpolation factor is hard-coded into said interpolation circuit.
9. The apparatus of claim 1, wherein said memory is a single port RAM.
10. The apparatus of claim 9, wherein said memory is divided into memory blocks such that during processing a first subset of memory blocks is in a Read mode and a second subset of memory blocks is in a Write mode.
11. The apparatus of claim 10, further comprising a plurality of despreaders.
12. The apparatus of claim 11, wherein each of said plurality of despreaders includes:
  - a selector circuit; and
  - a rake finger.
13. The apparatus of claim 12, wherein each of said memory blocks are divided into segments such that data stored in each segment is read out sequentially onto a bussing element accessible by multiple rake fingers via selector circuits in said plurality of despreaders.
14. The apparatus of claim 12, wherein said selector circuit includes a block multiplexer, a plurality of sample multiplexers, and a cache coupled to each rake finger.
15. The apparatus of claim 1, wherein said memory is a circular buffer.

16. The apparatus of claim 15, wherein said circular buffer includes multiple registers.
17. The apparatus of claim 16, further comprising a plurality of despreaders.
18. The apparatus of claim 17, wherein each of said plurality of despreaders includes:
- a selector circuit; and
  - a rake finger.
19. The apparatus of claim 18, wherein data stored in said multiple registers are accessible by multiple rake fingers via selector circuits in said plurality of despreaders.
20. The apparatus of claim 18, wherein said selector circuit includes a first set of multiplexers for selecting in-phase data, a second set of multiplexers for selecting quadrature data, and multiple sample select lines coupled to each rake finger.
21. A method for processing data in a spread spectrum system, comprising the steps of:
- receiving data at a sampling rate;
  - decimating said sampling rate by a decimation factor to obtain a decimated rate;
  - storing said data into a memory at said decimated rate;
  - interpolating said decimated rate to obtain an interpolated rate; and
  - outputting said data from said memory at said interpolated rate to a communication processor.
22. The method of claim 21, further comprising the step of:
- retrieving data from said memory in accordance with instructions from a micro-processor.

23. The method of claim 21, further comprising the step of:  
retrieving data from said memory in accordance with instructions from a  
dedicated controller.
24. An apparatus for processing data, comprising:  
a plurality of rake fingers;  
a memory for storing data at the input to said plurality of rake fingers; and  
a selector circuit positioned between said memory and each of said plurality of  
rake fingers;  
wherein said plurality of rake fingers can access said memory substantially  
simultaneously via a respective selector circuit.
25. The apparatus of claim 24, wherein said memory is a circular buffer including  
a plurality of registers.
26. The apparatus of claim 24, wherein said selector circuit includes a first  
plurality of multiplexers for selecting in-phase data from said memory, a second  
plurality of multiplexers for selecting quadrature data from said memory, and a set of  
select lines for controlling data being selected by said first plurality of multiplexers  
and said second plurality of multiplexers.
27. The apparatus of claim 24, wherein said memory is a single-port RAM.
28. The apparatus of claim 27, wherein said memory is divided into memory  
blocks such that, during each processing cycle, a first subset of said memory blocks is  
in a Read mode and a second subset of said memory blocks is in a Write mode.
29. The apparatus of claim 28, wherein each of said memory blocks is divided into  
segments, such that data stored in each segment is read out sequentially onto a bussing  
element.

30. The apparatus of claim 29, wherein said selector circuit includes a block multiplexer, a plurality of sample multiplexers, and a cache coupled to each rake finger.
31. The apparatus of claim 30, wherein said block multiplexer selects a bussing element to receive data from a segment.
32. The apparatus of claim 31, wherein said sample multiplexers selects data received from said block multiplexer and stores said data into said cache.
33. An apparatus for processing data in spread spectrum systems, comprising:  
a memory coupled to a set of despreaders via a bus;  
each of said set of despreaders including:  
a block multiplexer coupled to said bus;  
a set of sample multiplexers coupled to said block multiplexer;  
a cache coupled to said sample multiplexers; and  
a rake finger coupled to said cache; and  
wherein said set of despreaders can access samples stored in said memory substantially simultaneously via said bus.
34. The apparatus of claim 33, wherein said memory is divided into blocks such that during a processing cycle by a despreaders, a first subset of said blocks is in a Read mode and a second subset of said blocks is in a Write mode.
35. The apparatus of claim 34, wherein said blocks are divided into segments such that samples stored in each of said segments are read out sequentially onto a bussing element coupled to said bus.
36. The apparatus of claim 35, wherein said block multiplexer in each of said despreaders selects samples from one bussing element.

